

Aspera

VISTA
ANALOG WALKIE TALKIE



RUGGED BODY
HIGH PERFORMANCE TWO WAY RADIO

Specific

- Led Display Logo
- 16 Channel
- 446.000~446.2000Mhz
- 50, CTCSS, 105 Dcs
- TOT Function
- Auto Save Battery
- VOX Function
- Low Power Remind
- Scan Function
- Free License
- Scramble Function
- Companding Function
- PC Programming
- Fluorescent Color
- Alarm Function

General Function	
Frequency Range	446.000~446.2000Mhz
Battery Voltage	DC7.4V
Channel Capacity	16
Antenna Impedance	50Ω
Weight	450g(Including Battery & Antenna)
PLL Channel Spacing	12.5kHz/25KHz
Battery Capacity	4200 mAh
Dimensions (without Antenna)	130×33×56mm
Transmitter	
Modulation Type	16KΦF3E/8KΦF3E
Maximum Deviation	25K≤5kHz 12.5K≤2.5kHz
Frequency Stability	±2.5ppm
Modulation Distortion	≤5%
FM Ham And Noise	-45dB
Intermodulation	67dB
RF Power Output	0.5w
Receiver	
Sensitivity	<0.16uV(12dB SINAD)
Squelch Selectivity	<0.2uV
Adjacent Channel Selectiivity	25K≥65dB 12.5K≥60dB
Spurious Rejection	≥80dB
Image Rejection	25K≥45dB 12.5K≥40dB
AF Outpower	≥0.5W
Audio Distortion	≤5%
Audio Power	1W
Environment	
Work Temperature	-20℃~+65℃
Save Temperature	-20℃~+70℃
Standard	According GJB 150-2009 & MIL-STD-810 C/D/E/F/G Standard

*The above specifications are tested in accordance with the TIA/EIA-603 standard. Due to the continuous updating of the technology, the above indicator data will be changed without notice.